



Datos útiles sobre el sistema [ZeroDew](#):

- Valores de resistencia, amperaje y consumo al máximo de potencia y longitud total útil (con resistencia):

*Buscador 50mm:	32 Ohm, 0.37A, 4.5W	19 cm
*Buscador 80mm:	20 Ohm, 0.60A, 7.2W	29 cm
*Ocular 2":	32 Ohm, 0.37A, 4.5W	21 cm
*Tubo 80mm:	17,5 Ohm, 0.68A, 8.2W	32 cm
*Tubo 100/110mm:	14 Ohm, 0.86A, 10.3W	41 cm
*Tubo 120/125mm:	12 Ohm, 1A, 12W	47 cm
*Tubo 6":	8 Ohm, 1.5A, 18W	64 cm
*Tubo 7"/8":	7.6 Ohm, 1.6A, 19W	74 cm
*Tubo 9"/10":	6.2 Ohm, 1.9A, 23W	94 cm
*Tubo 11"/12":	5.5 Ohm, 2.2A, 26W	109 cm
*Tubo 14":	5 Ohm, 2.4A, 28W	127 cm
*Tubo 16":	4.4 Ohm, 2.7A, 33W	142 cm